

Postup montáže svítidla BANDO-LED

1. Vyndejte svítidlo z transportního obalu.
2. Zapojte napájecí kabel do EP:

B A N D O G-LED
 na svorku 1 - fázový vodič
 na svorku N - nulový vodič

MULTI B A N D O G-LED
 na svorku 1 - dobíjecí fázový vodič
 na svorku 2 - spínaný fázový vodič
 na svorku N - nulový vodič
 na svorku ⊕ - ochranný vodič

3. Svítidlo nasuňte do předem vyříznutého montážního otvoru v podhledu o průměru:
 BANDO-LED-800 - 113mm
 BANDO-LED-1700 - 162mm
 BANDO-LED-3000 - 208mm
4. Pomocí pružných úchytlů (pouze u modelu BANDO-LED-800) upevněte svítidlo v podhledu.
 Při montáži svítidel: BANDO-LED-1700 a BANDO-LED-3000 sejměte rámeček ze svítidla, úchyty otočte směrem ke svítidlu a vsuňte do podhledu, po té začněte utahovat šrouby úchytlů dokud se nedotknou podhledu.
 Po té vraťte rámeček zpět na svítidlo.

Nedotýkat se LED ! Při montáži dodržujte ESD bezpečnost!

Upozornění pro montáž svítidel BANDO-LED

Svítidlo smí na elektrickou síť připojovat pouze osoba s odpovídající kvalifikací dle platné vyhlášky o odborné způsobilosti v elektrotechnice.

Výrobce je zařazen do systému zpětného odběru elektrozařízení a elektroodpadu dle platných vyhlášek a nařízení.

Výrobce je zařazen do systému zpětného odběru a recyklace obalů firmy EKO-KOM. (EK-F06070058)

Při nedodržení montážního návodu výrobce neručí za případné vzniklé škody!

Zapuštěná svítidla nevhodná pro připevnění do/na normálně hořlavé povrchy, pokud tepelně izolační materiál může zakrývat svítidlo.



Údržba:

Konstrukce svítidla nevyžaduje zvláštní údržbu. Znečištěné těleso omyjeme vlažnou vodou s přidavkem saponátového čisticího prostředku. Mřížku svítidla a reflektor je možné očistit nemastným stlačeným vzduchem.

Mounting instruction for series BANDO-LED

1. Take the fixture from transporting packing.
2. Connect supply cable electronic ballast:

B A N D O G-LED
 on terminal 1 - phase conductor
 on terminal N - neutral conductor

MULTI B A N D O G-LED
 on terminal 1 - charging phase conductor
 on terminal 2 - swithing phase conductor
 on terminal N - neutral conductor
 on terminal ⊕ - protective conductor

3. Install the fixture into prepared outlet in false ceiling in deiametr:
 BANDO-LED-800 - 113mm
 BANDO-LED-1700 - 162mm
 BANDO-LED-3000 - 208mm
4. Fix the luminaire in the ceiling using the flexible clamps (only the BANDO-LED-800 model).
 mounting luminaires: BANDO-LED-1700 and BANDO-LED-3000, remove the frame from the luminaire, turn the handles towards the light and slide into the ceiling, then tighten the fastener bolts until they touch the ceiling. Then return the frame back to the luminaire

Do not touch the LED! When mounting, observe ESD safety!

Warning for mounting series BANDO-LED

The fitting can be installed by authorised person only.

Producer included into EKO-KOM (EK-F06070058) recycling system.

In case of instruction non-performance producer can not be responsible for relevant damages caused !

Recessed luminaires not suitable for mounting in/on normally flammable surfaces when thermally insulating material may cover the luminaires.

Maintenance :

Construction does not need any special maintenance. It can be cleaned with water and damp duster with detergent.

